# **Support Vector Machines:** Duality and Leave-One-Out

CS4780/5780 - Machine Learning Fall 2013

> Thorsten Joachims Cornell University

Reading: Schoelkopf/Smola Chapter 7.3, 7.5 Cristianini/Shawe-Taylor Chapter 2-2.1.1

#### (Batch) Perceptron Algorithm

Input:  $S = ((\vec{x}_1, y_1), ..., (\vec{x}_n, y_n)), \ \vec{x}_i \in \Re^N$ ,  $y_i \in \{-1, 1\}$ ,

## Dual (Batch) Perceptron Algorithm

```
Input: S = ((\vec{x}_1, y_1), ..., (\vec{x}_n, y_n)), \ \vec{x}_i \in \Re^N, \ y_i \in \{-1, 1\}, I \in [1, 2, ..]
```

#### SVM Solution as Linear Combination

· Primal OP:

$$\begin{array}{ll} \text{minimize:} & P(\vec{w},b,\vec{\xi}) = \frac{1}{2} \, \vec{w} \cdot \vec{w} + C \, \sum_{i=1}^n \xi_i \\ \text{subject to:} & \forall_{i=1}^n : y_i [\vec{w} \cdot \vec{x}_i + b] \geq 1 - \xi_i \\ & \forall_{i=1}^n : \xi_i \geq 0 \end{array}$$

• Theorem: The solution  $\overrightarrow{w}^*$  can always be written as a linear combination

$$\vec{w}^* = \sum_{i=1}^n \alpha_i y_i \vec{x}_i$$

of the training vectors with  $0 \le \alpha_i \le C$ .

- Properties:
  - Factor α, indicates "influence" of training example (x,y,).
  - If  $\xi_i > 0$ , then  $\alpha_i = C$ .
  - If 0 ≤ α<sub>i</sub> < C, then ξ<sub>i</sub> = 0.
  - (x<sub>i</sub>, y<sub>i</sub>) is a Support Vector, if and only if α<sub>i</sub> > 0.
  - If  $0 < \alpha_i < C$ , then  $y_i(x_i w^* + b) = 1$ .
  - SVM-light outputs  $\alpha_i$  using the "-a" option

## **Dual SVM Optimization Problem**

Primal Optimization Problem

minimize: 
$$P(\vec{w}, b, \vec{\xi}) = \frac{1}{2} \vec{w} \cdot \vec{w} + C \sum_{i=1}^{n} \xi_i$$
 subject to: 
$$\forall_{i=1}^{n} : y_i [\vec{w} \cdot \vec{x}_i + b] \geq 1 - \xi_i$$
 
$$\forall_{i=1}^{n} : \xi_i \geq 0$$

· Dual Optimization Problem

$$\begin{array}{ll} \text{maximize:} & D(\vec{\alpha}) = \sum\limits_{i=1}^{n} \alpha_i - \frac{1}{2} \sum\limits_{i=1}^{n} \sum\limits_{j=1}^{n} y_i y_j \alpha_i \alpha_j (\vec{x}_i \cdot \vec{x}_j) \\ \text{subject to:} & \sum\limits_{i=1}^{n} y_i \alpha_i = 0 \\ & \forall_{i=1}^{n} : 0 \leq \alpha_i \leq C \end{array}$$

Theorem: If  $w^*$  is the solution of the Primal and  $\alpha^*$  is the solution of the Dual, then

$$\overrightarrow{w}^* = \sum_{i=1}^n \alpha_i^* y_i \overrightarrow{x}_i$$

#### Leave-One-Out (i.e. n-fold CV)

- Training Set:  $S = ((x_1, y_1), \dots, (x_n, y_n))$
- Approach: Repeatedly leave one example out for testing.


Train on	Test on
$(x_2,y_2), (x_3,y_3), (x_4,y_4),, (x_n,y_n)$	(x <sub>1</sub> ,y <sub>1</sub> )
$(x_1,y_1), (x_3,y_3), (x_4,y_4),, (x_n,y_n)$	(x <sub>2</sub> ,y <sub>2</sub> )
$(x_1,y_1), (x_2,y_2), (x_4,y_4),, (x_n,y_n)$	(x <sub>3</sub> ,y <sub>3</sub> )
$(x_1,y_1), (x_2,y_2), (x_3,y_3),, (x_{n-1},y_{n-1})$	$(x_n,y_n)$


- Estimate:  $Err_{loo}(A) = \frac{1}{n} \sum_{i=1}^{n} \Delta(h_i(x_i), y_i)$
- Question: Is there a cheaper way to compute this estimate?


## Necessary Condition for Leave-One-Out Error


- Lemma: For SVM,  $[h_i(\vec{x}_i) \neq y_i] \Rightarrow [2\alpha_i R^2 + \xi_i \geq 1]$
- Input:
  - $\alpha_i$  dual variable of example i
  - $-\xi_i$  slack variable of example i
  - $\|\vec{x}_i\| \le R$  bound on length
- Example:

Value of 2 $\alpha_i R^2 + \xi_i$	Leave-one-out Error?
0.0	Must be Correct
0.7	Must be Correct
3.5	Error
0.1	Must be Correct
1.3	Correct









#### Fast Leave-One-Out Estimation for SVMs Lemma: Training errors are always Leave-One-Out Errors. Algorithm: - $(R,\alpha,\xi)$ = trainSVM( $S_{train}$ ) $- \ \ FOR \ (x_i,y_i) \in S_{train}$ • IF $\xi_i$ >1 THEN loo++; ELSE IF (2 α<sub>i</sub> R² + ξ<sub>i</sub> < 1) THEN loo = loo;</li> • ELSE trainSVM(S $_{train} \setminus \{(x_i,y_i)\})$ and test explicitly Experiment: **Training Data** Retraining Steps (%) Reuters (n=6451) 0.58% 32.3 WebKB (n=2092) 20.42% 235.4 Ohsumed (n=10000) 2.56% 1132.3